

LICENSE FREE

Aspera

HIGH PERFORMANCE TWO WAY RADIO

Wide/narrow bandwidth / COMP function
VOX functions / End tone elimination
Scanning function / Power saving function

V7



CTCSS/DCS
16 channels

PMR446 FM Transceiver

VOICE SCAMBLER 2.COMPANDER 3. 360 DEGREE MICROPHONE

V7

PMR446 FM Transceiver

Aspera

HIGH PERFORMANCE TWO WAY RADIO

Main Functions

- 16 channels
- PC Programmable
- VOX functions
- CTCSS/DCS
- English voice prompt
- Power saving function
- Scanning function
- Scrambler
- COMP function
- Wide/narrow bandwidth selective
- End tone elimination
- Emergency alarm

General		Transmitter		Receiver	
frequency range	UHF PMR446MHz	RF Output power	UHF 0.5W	Receiving sensitivity	<0.2µV
Operating temperature	-20℃~+50℃	Frequency stability	± 2.5ppm	Audio distortion	≤5%
Operating voltage	DC 7.2V	Modulation Limiting	≤2.5KHz	Audio response	+2dB~-10dB
Operate mode	Simplex or Semi-duplex	Audio distortion	≤5%	Co-channel suppression	≥-8dB
Antenna impedance	50Ω	Modulation character	+3dB~-3dB	Adjacent Ch. selectivity	≥ 55dB
Weight	190g(Include battery & antenna)	Adjacent Ch. power	≥ 65dB	Intermodulation rejection	≥ 55dB
Dimensions (WxHxD)	116x57x34mm	Spurious radiation	≤ 7.5µW	Spurious response	≥ 65dB
		Occupied bandwidth	≤ 16KHz	Blocking	≥ 85dB

Standard Accessories



Optional Accessories



More accessories please refer to our website.

AUTHORIZED DEALER
LINKWELL TELECOM SERVICES.
1/4, Puranik Building, Near Old Post Office,
Parvel, Navi Mumbai, Maharashtra, India-410 206.
Tel. No. : 022-27462199.
www.linkwelltelecom.com

